

BLADE FUSE TERMINAL BLOCKS DIN RAIL MOUNT


MORSETTITALIA


- Push in various circuit protection devices including auto blade fuses or bladed circuit breakers.
- Blocks can facilitate plug in modules. Module options include diodes, MOV's and cartridge fuses.
- Disconnector options include bladed plug or knife type for on / off switching of a circuit.
- Single or multiple pole terminal blocks with optional insulated and dividable jumper.
- Standard termination screw terminals. Optional screw-less spring terminals or hybrid terminals.
- Marking accessories are a available for both the blocks and cables.



Screw Terminals







Part Number	Description	Ampere / Volt Rating	Colour	Dimensions in MM L	H	W
4358100	Auto blade fuse module 0.5mm² to 4mm² (#24-10AWG)	25A, 300V		58.9	29.5	6
4358101	Auto blade fuse module 0.5mm² to 4mm² + 12V LED	25A, 12V		58.9	29.5	6
4358102	Auto blade fuse module 0.5mm² to 4mm² + 24V LED	25A, 24V		58.9	29.5	6
435K0000	Disconnector (Plug in type) Orange	25A, 300V		19.2	20.4	5
43444	End stop (Stops modules sliding).	-		55	34	6
43585	Separator / End plate (1.5mm wide) ^	-		55	33	1.5
4358630	Separator / End plate (3.0mm wide) ^	-		55	33	3.0
43506/22	Insulated jumper 22 pole (Pitch 6.1mm) JB6	25A, 600V		-	-	-
43509/12	Insulated jumper 12 pole (Pitch 9.1mm) ^ Jb9	25A, 300V		-	-	-
43300	Marking tags. Printed No. 1-10 (2 sets)	-		11.9	-	4.8
43310	Marking tags. Printed No. 1-100 (1 set)	-		11.9	-	4.8
43311	Marking tags. Printed No. 101-200 (1 set)	-		11.9	-	4.8
43192	Marking tags. Blank stem. 1 stem = 20 Marking tags.	-		11.9	-	4.8

Mounting: DIN Rail 35 **Connection:** Screw standard. Optional cage clamp or hybrid connection.
Optional Components: Mini fuse module, non-fused terminal block modules and Euro Omega DIN 35 Rails.
Jumpers: Jumpers can be used to share power from one input cable across multiple fuse modules and are supplied in strips of 12. They can be cut using the ratchet jumper cutting tool #43517. ^ One x 3.0mm or two x 1.5mm separator / end plates are required between each fuse module when using jumpers. Sectional and side-inserted.
Fuse Modules: Feature 1 x open and 1x closed wall so only 1 x end plate is required to finish either a single module or multiple modules. Fuse modules accept both auto blade fuses and auto blade circuit breakers. Cartridge fuses can be fitted by purchasing the appropriate fuse holder module which plugs directly into the fuse module.
Fuse Holders: *One x 1.5mm separator / end plate is required between each adjoining fuse module.
End Stop: These modules feature a screw which tightens onto the DIN rail to stop modules sliding along the rail.


Auto Fuse 1A - 30A 32VDC
LED Auto Fuse 3A - 30A 32VDC
See page 17



Auto Blade Circuit Breakers
Automatic & Manual Reset
See page 49 - 50



Blade Fuse / Breaker Modules
Wire fixing: 2 x screw connectors.
Optional 12V / 24V LED indicator.



Disconnector
Plug type. Tool less.
Push in / pull out.



Separator / End Plates
Separates terminal blocks.
Completes a row.
1.5mm or 3.0mm width options.



End Stop
Fitted to each end of a row of terminal blocks. Stops modules sliding on DIN rail. Screw down.



Ratchet Tool Cuts
Side inserted plug in jumpers.
P/N: 43516 cuts jumper 6.1mm pitch
P/N: 43517 cuts jumper 9.1mm pitch



Optional Plug In Module Options
Cartridge fuse module. M205 or 3AG.
MOV / Surge supply module V130LA2.
Diode modules. Contact sales.



PROLEC
Email: info@prolecproducts.com.au
Web: www.prolecproducts.com.au